Application for United States Letters Patent

for

Discharging Envelope Detector

by

Lior Horwitz

Noam Avni

and

Simoni Ben-Michael

Seth Z. Kalson
Intel Corporation

Field

The present invention relates to analog circuits, and more particularly, to an envelope detector circuit for use in a communication system.

Background

5   The Home Phoneline Networking Alliance (HomePNA) is an incorporated, non-profit association of companies working to bring networking technology to the home. See www.homepna.org. HomePNA envisions bringing Ethernet technology to the home by utilizing existing home phone wiring for the network physical medium. HomePNA provides specifications for the physical layer (PHY), its interface to an Ethernet MAC

10   (Media Access Control), and its interface to the home phone wiring. See the IEEE (Institute of Electrical and Electronic Engineers) 802.3 standard for Ethernet.

The position of a HomePNA PHY in relationship to the OSI (Open Systems Interconnection) model is illustrated in Fig. 1. Logical Link Control (LLC) **102** and MAC **104** are implemented in accordance with IEEE 802.3, and HomePNA PHY **106**

15   communicates with MAC **104** via interface **108**. Additional sublayers, and other optional layers, may be added to the layers shown in Fig. 1 so that PHY **106** may provide services to other communication protocols, such as Gigabit Ethernet. In practice, PHY **106** and MAC **104** may be integrated on a single die, so that interface **108** is not readily visible.

PHY **106** receives a MAC frame from MAC **104**, strips off the 8 octets of

20   preamble and delimiter from the MAC frame, adds a HomePNA PHY header to form a HomePNA PHY frame, and transmits a PHY frame on physical medium **108**. Fig. 2 illustrates HomePNA PHY framing. A PHY frame comprises Ethernet Packet **202**, and appended to Ethernet Packet **202** is a HomePNA PHY header, comprising SYNC interval **204**, Access ID (Identification) **206**, Silence interval **208**, and PCOM field **210**.

25   A PHY frame is transmitted on physical medium **108** utilizing pulse position modulation (PPM). All PHY symbols transmitted on physical medium **108** comprise a pulse formed of an integer number of cycles of a square wave that has been filtered with a bandpass filter. The position of the pulse conveys the transmitted symbol. Differential signaling is employed, in which a pulse and its negative are transmitted on two wires for

30   each transmitted symbol. However, for simplicity of discussion, we consider only one component of the differential signal when describing the signal waveform.

As indicated in Fig. 2, transmission begins with SYNC symbol 0, and Access ID field **206** is coded into seven AID (Access ID) symbols. SYNC symbol 0 may also be denoted as AID symbol 0. Access ID symbols 1 through 4 are used to identify individual stations to enable reliable collision detection. Access ID symbols 5 and 6 are used to transmit remote control management commands. AID symbol 7 is a silence interval.

SYNC symbol 0 and each AID symbol are 129 tics long, where 1 tic is defined as $(7/60)10^{-6}$ seconds, which is approximately 116.667 nanoseconds. AID symbols 1 through 7 begin with a blanking interval of 60 tics, followed by a pulse positioned within one of four time slots to convey two bits of information. The time slots are separated by 20 tics, and are at positions 66, 86, 106, and 126 tics from the beginning of an AID symbol interval. SYNC symbol 0 is composed of a SYNC_START pulse beginning at tic = 0 and a SYNC_END pulse beginning at tic = 126.

In the example of Fig. 2, AID symbols 1 through 4 represent the Access ID word 00101101, where AID symbol 1 represents AID0 = 1 and AID1 = 0, AID symbol 2 represents AID2 = 1 and AID3 = 1, AID symbol 3 represents AID4 = 0 and AID5 = 1, and AID symbol 4 represents AID6 = 0 and AID7 = 0. AID symbols 5 and 6 represent the control word 0001, where AID symbol 5 represents Ctrl0 = 1 and Ctrl1 = 0, and AID symbol 7 represents Ctrl2 = 0 and Ctrl3 = 0.

A collision is detected only during AID symbols 0 through 7. If a transmitting station reads back an AID value that does not match its own, then a collision is indicated, and a JAM signal is transmitted to alert other stations. Non-transmitting stations may also detect non-conforming AID pulses as collisions. Only a transmitting station emits a JAM signal.

Examples of transmitted and received pulses for three AID symbols are indicated in Figs. 3 and 4, respectively. In Fig. 4, SYNC_START and SYNC_END pulses indicate AID symbol 0. AID symbol 1 comprises a pulse in position 1 (tic = 86), and AID symbol 2 comprises a pulse at position 2 (tic = 106). A receiving PHY performs full-wave rectification of a received signal, and compares the envelope of the rectified signal with an AID slice threshold. The PHY detects a received pulse if its envelope exceeds the AID slice threshold. As soon as a pulse is detected by a PHY, the PHY disables further indications of detection until a time AID_END_BLANK (located at tic = 61) from the

beginning of the pulse, after which detection indication must be re-enabled for the next received pulse.

As indicated in Fig. 2, the data symbols in a PHY frame comprise two receiver training symbols, PCOM symbols, and symbols coding Ethernet packet **202**. (PCOM
5   symbols are reserved for future use to be used by a local management entity, and are ignored by the PHY.) Referring now to Fig. 5, a data symbol interval begins with the beginning of a pulse, which defines tic = 0 for the symbol interval. Symbol timing (in tics) is measured from tic = 0. Except for the first data symbol interval, the beginning of a data symbol time interval is marked by the position of the pulse for the previous data ·
10   symbol. The position of a pulse relative to the beginning of its time interval conveys the symbol information. Each position is separated by one tic. When a pulse begins transmission, the previous symbol interval ends and a new one immediately begins. Time intervals for data symbols are therefore variable, depending upon the transmitted data.

For example, as shown in Fig. 5, the beginning of the first data symbol interval is
15   indicated by START_TX_PULSE at tic = 0, and the information conveyed by Data Symbol 1 is indicated by the position of Pulse 1 in Fig. 5. Pulse 1 then defines the beginning of the time interval for the next data symbol, Data Symbol 2.

Data receive timing is indicated in Fig. 6. In the example of Fig. 6, data symbol intervals for Data Symbol 1 and Data Symbol 2 are illustrated. The received waveform is
20   formed from the transmitted pulse, along with any distortions and reflections that occur in the wiring network. The PHY detects the point at which the envelope crosses a threshold, denoted by Data_Slice_Threshold. Immediately after threshold detection, the PHY disables indication of detection for a time period END_DATA_BLANK, which is equal, in tics, to pulse position number 0 minus 3. Detection indication is enabled after
25   END_DATA_BLANK.

Thus, as indicated in Figs. 4 and 6, a HomePNA PHY requires proper envelope detection of received waveforms. Envelope detection usually involves full-wave rectification followed by integration, where the integration is often performed by charging a capacitor. However, noise spikes on the home telephone network may lead to
30   detection error. A detection error may result in inaccurately estimating pulse position (timing jitter), leading to incorrect symbol decoding. A detection error may also result in

a detection being declared when no pulse was actually transmitted by another station, i.e., a false alarm. A detection error may also result in the failure to declare a detection when a pulse was in fact transmitted.

Using large capacitors for signal integration may reduce detection error. Furthermore, in many prior art envelope detectors, the integrating capacitor is always being discharged by a discharge resistor. However, this type of discharging may cause output ripple, which may lead to timing jitter or an increase in the false alarm rate. Using a large capacitor, or providing for a longer discharge time, may reduce ripple.

However, using large capacitors, and using long discharge times, lead to various problems. In custom VLSI (Very Large Scale Integration) technology, large capacitors are expensive in terms of die area. Furthermore, the integrating capacitor should be discharged before the next arriving pulse, otherwise a slow discharging time may lead to detection error. Embodiments of the present invention address these problems, and are well suited to network communication utilizing home phone wiring as envisioned by the Home Phoneline Networking Alliance.

Brief Description of the Drawings

Fig. 1 illustrates the position of a HomePNA PHY within the OSI communication protocol stack.

Fig. 2 illustrates HomePNA PHY framing.

Fig. 3 illustrates waveforms and timing for three transmitted Access ID symbols.

Fig. 4 illustrates waveforms and timing for three received Access ID symbols.

Fig. 5 illustrates waveforms and timing for two transmitted data symbols.

Fig. 6 illustrates waveforms and timing for two received data symbols.

Fig. 7 is a high-level circuit according to an embodiment of the present invention.

Fig. 8 is a more detailed circuit according to the embodiment of Fig. 7.

Fig. 9 is a high-level circuit according to another embodiment of the present invention.

Description of Embodiments

Fig. 7 provides a high-level circuit model of an embodiment of the present invention. Capacitor **702** is an integrating capacitor that is charged by current sink **704**. Current sink **704** is a voltage controlled current sink responsive to input voltage V_{in} at

input terminal (or port) **706**. Input voltage V_{in} may be a differential input voltage, although only one terminal to current sink **704** is explicitly shown. Input voltage V_{in} is the voltage propagated on physical medium **108** (the home phone lines) and received by a PHY.

5   Current sink **704** performs full-wave rectification, so that when a pulse is received by the PHY, the current drawn (sunk) at node **708** by current sink **704** is indicative of the rectified received pulse. While capacitor **702** is being charged, pMOSFET **710** (p-Metal Oxide Semiconductor Field Effect Transistor) is OFF. Because capacitor **702** serves as an integrator, the voltage at node **708** is indicative of the envelope of the received pulse

10 when capacitor **702** is being charged by current sink **704**.

   Transistor **714**, along with current mirror transistors **716** and **718** biased by a reference current I_{ref}, comprise a high input impedance buffer to sample the envelope voltage at node **708**, so that the output voltage, V_{out}, at node **720** is indicative of the envelope voltage at node **708**. Capacitor **722** serves as a lowpass filter, and resistors **724**

15 and **726** serve as a voltage divider to provide a DC voltage level shift.

   When the output voltage V_{out} at node **720** exceeds a threshold (e.g., AID_Slice_Threshold during the AID portion of the received PHY frame, or Data_Slice_Threshold during the data symbol portion of the received PHY frame), signal line DSCRG_ENV_L connected to the gate of pMOSFET **710** is switched LOW so that

20 pMOSFET **710** is switched ON to discharge capacitor **702**. With pMOSFET **710** switched ON, pullup pMOSFET **712** acts as a voltage controlled current source to node **708**, so that the potential difference across capacitor **702** is reduced, thereby discharging capacitor **702**.

   Using pullup pMOSFET **712** to discharge capacitor **702** provides for faster

25 discharging than using a discharge resistor, thereby providing for a low detection error. However, it is found that for the HomePNA networking environment, in many instances V_{out} drops too low (it has an inverted spike) if capacitor **702** is discharged too quickly by pullup pMOSFET **712**, and this may cause signal interference with other circuit elements of the PHY. To remedy this problem, current sink **728** is provided.

30   Current sink **728** is connected to node **708** via serially connected transistors **730** and **710**. Transistor **730** is switched ON by setting HIGH signal line EN_FINE_DSCRG.

With EN_FINE_DSCRG set HIGH, current sink **728** is enabled in the sense that it sinks current from node **708** to ground when DSCRG_ENV_L is switched LOW.

Suppose current sink **728** is enabled (EN_FINE_DSCRG set HIGH). As the voltage at node **708** is brought lower due to capacitor **702** being charged by current sink
5   **704**, pullup pMOSFET **712** switches ON and supplies drain current to current sink **728** via nMOSFET **730**. When DSCRG_ENV_L is switched LOW due to the voltage V_{out} at node **720** exceeding a threshold (e.g., detection of a pulse), the voltage at node **708** starts to rise as capacitor **702** is being discharged by pMOSFET **712**. Because the gate of pMOSFET **712** is connected to node **708**, the rising voltage at node **708** causes
10   pMOSFET **712** to conduct less drain current. This results in a larger fraction of the current being sunk by current sink **728** to be drawn from capacitor **702**, so that the discharge rate of capacitor **702** is slowed down. The net effect of pMOSFET **712** in combination with current sink **728** is to allow for a "fine" discharge of capacitor **702**, so that the output voltage V_{out} transitions from a high level indicative of capacitor **702** being
15   charged to a low level indicative of capacitor **702** being discharged without having an inverted spike.

Fig. 8 provides a more detailed circuit of the embodiment of Fig. 7, where like numerals among Figs. 7 and 8 denote similar circuit components. A differential voltage input signal is applied to input terminals **802** and **804**. The circuit components within
20   dashed box **806** comprise a differential amplifier, providing a differential output voltage on lines **808** and **810**, and an output voltage on line **812**.

The circuit components within dashed boxes **704** and **728** serve as voltage-controlled current sinks, and are controlled by the voltages on lines **808, 810,** and **812** so as to provide current sinks indicative of $|V_H - V_L|$, the magnitude of the difference
25   between the input voltages at input terminals **802** and **804**. As indicated in Fig. 8, voltage-controlled current sink **702** is comprised of the differential transistor pair **850** and **852** cascaded with current sink transistor **854**, and voltage-controlled current sink **728** is comprised of the differential transistor pair **856** and **858** cascaded with current sink transistor **860**. Thus, in Fig 7, current sink **728** may be a voltage-controlled current sink
30   similar to that of current sink **704** in that the current sunk by current sink **728** is indicative of the full-wave rectified received waveform.

The circuit components within dashed box **814** provide a bias voltage to the current mirror transistors **816**, **818**, **820**, **822**, and **824**. Transistor **818** provides a bias current to transistor **826**, where transistors **826**, **828**, and **830** comprise a current mirror. Transistor **830** provides a bias current to transistor **832**. Transistor **832** biases transistors

5   **834**, **836**, and **838**. With transistor **840** OFF (EN_DSCRG is HIGH), transistors **834**, **836**, and **838** provide current to current sink **704**. If transistor **840** is ON (EN_DSCRG is LOW), then transistors **834** and **836** are bypassed and transistor **838** supplies more current to current sink **704** than when transistor **840** is OFF. Supplying more current to current sink **704** will cause integrating capacitor **702** to be charged at a slower rate by

10   current sink **704**, and thus EN_DSCRG allows for adjustment of the charging rate of integrating capacitor **702** due to current sink **704**.

As capacitor **702** becomes charged, it provides less current to current sink **704**. But as capacitor **702** charges, the node voltage at node **708** decreases, so that pMOSFET **842** supplies more current to current sink **704** so as to offset the reduction in current

15   supplied by capacitor **702**.

Variations may be made to the described embodiments without departing from the scope of the claims concluding this specification. For example, another embodiment is illustrated in Fig. 9, which functions in similar fashion to that of Fig. 7, but where pulldown transistor **904** is used instead of pullup transistor **712**, and where current

20   sources **902** and **910** are used instead of current sinks **704** and **728**. For the embodiment of Fig. 9, integrating capacitor **702** is charged by current source **902** when nMOSFET **906** is OFF. After capacitor **702** is charged such that the output voltage V_{out} exceeds some threshold, pulldown transistor **904** discharges capacitor **702** when nMOSFET **906** is switched ON. When nMOSFET **908** is switched ON, the combination of pulldown

25   nMOSFET **904** with current source **910** helps to prevent spikes in the output voltage V_{out}, as described earlier regarding Fig. 7.

As is understood from the embodiments of Figs. 7 and 9, current sources may be used instead of current sinks. Consequently, in the claims concluding this specification, it is to be understood that the term "current source" may mean a current source or a current

30   sink.